

VIDEO IF+SIF SYSTEM

The KA2914A, KA2918 are silicon monolithic integrated circuits designed for the VIF and SIF stage in color and B/W television receivers.

KA2914A: for Reverse AGC type

KA2918: for Forward AGC type

FUNCTIONS**VIF**

- Three controlled IF amplifier stages
- Video demodulator controlled by picture carrier
- Black noise and white noise inverter • Peak AGC.
- DC amplifier for RF AGC out

SIF

- Three differential IF amplifier stages • Phase detector
- DC controlled attenuator
- Audio amplifier stage with NFB terminal

FEATURES

- PIF, SIF, ATT audio driver
- 2 chip color TV system is possible with the KA2153 or KA2154


VIF

- High gain, wide band IF amplifier
- AGC characteristics with excellent stability
- Excellent DG/DP characteristics
- Excellent S/N characteristics due to delayed 3-stage AGC action
- Negative video output signal
- Switch off the video part with VTR SW

SIF


- Excellent limiter characteristics
- Excellent attenuator characteristics

24 DIP

**ORDERING INFORMATION**

Device	Package	Operating Temperature
KA2914A	24 DIP	- 20 ~ + 65°C
KA2918		

BLOCK DIAGRAM

ABSOLUTE MAXIMUM RATINGS ($T_a = 25^\circ\text{C}$)

Characteristic	Symbol	Value	Unit
Supply Voltage	V_{CC}	15	V
Terminal 11 Open Voltage	V_{11}	15	V
Video DC Output Current	I_{15}	6	mA
Audio DC Output Current	I_3	3	mA
Terminal 2 Voltage	V_2	15	V
Power Dissipation (Note)	P_d	1.6	W
Operating Temperature	T_{opr}	-20 ~ 65	$^\circ\text{C}$
Storage Temperature	T_{stg}	-55 ~ 150	$^\circ\text{C}$

Note: Derated above $T_a = 25^\circ\text{C}$ in the proportion of 12.8 mW/ $^\circ\text{C}$.

ELECTRICAL CHARACTERISTICS

PIF Section ($T_a=25^\circ\text{C}$, $V_{CC}=12\text{V}$ $f_p=45.75\text{MHz}$, $f_s=41.25\text{MHz}$)

Characteristic	Symbol	Test Conditions	Min	Typ	Max	Unit	Test Fig
Recommended Supply Voltage	V_{CC}	—	10.8	12.0	13.2	V	—
Supply Current	I_{CC}	—	50	72	95	mA	1
Video DC Output Voltage	V_{15}	SW ₁ : 1 (KA2914A) SW ₂ : 2 (KA2918)	5.2	5.5	5.8	V	1
AFT DC Output Voltage	V_{13}	SW ₁ : 1 (KA2914A) SW ₂ : 2 (KA2918)	5.3	6.8	8.3	V	1
	V_{14}	SW ₁ : 1 (KA2914A) SW ₂ : 2 (KA2918)	5.3	6.8	8.3	V	1
AFT DC Offset Voltage	ΔV_{13-14}	SW: 1 (KA2914A) SW: 2 (KA2918)	-1.5	0	1.5	V	1
RF AGC Residual Output Voltage	$V_{11 \text{ Sat}}$	SW ₁ : 1 (KA2914A) SW ₂ : 2 (KA2918)	—	—	0.5	V	1
RF AGC Leak Current	$I_{11 \text{ LEAK}}$	SW ₁ : 1 (KA2918) SW ₂ : 1 (KA2914A)	—	—	1	μA	1
Video Sensitivity	V_i Pin 7-8	(Note 1)	60	150	250	μV_{rms}	2
AGC Range	ΔA_{VIF}	(Note 2)	60	64	—	dB	2
SYNC TIP Level Voltage	V_{SYNC} (V_{15})	(Note 3)	2.3	2.5	2.7	V	2
Max. IF Input Voltage	$V_{\text{IN Max}}$ PIF	(Note 4)	100	120	—	mV_{rms}	2
White Noise Threshold Level	V_{WTH} (V_{15})	(Note 5)	5.8	6.2	6.6	V	2
White Noise Clamp Level	V_{WCL} (V_{15})	(Note 5)	3.7	4.1	4.5	V	2

ELECTRICAL CHARACTERISTICS

PIF Section ($T_a = 25^\circ\text{C}$, $V_{CC} = 12\text{V}$, $f_p = 45.75\text{MHz}$, $f_s = 41.25\text{MHz}$)

Characteristic	Symbol	Test Conditions	Min	Typ	Max	Unit	Test Fig
Black Noise Threshold Level	V_{BTH} (V_{15})	(Note 5)	1.4	1.6	1.8	V	2
Black Noise Clamp Level	V_{BCL} (V_{15})	(Note 5)	2.9	3.3	3.7	V	2
Video Frequency Response	f_{BW}	(Note 6)	4.5	5.5	—	MHz	3
Suppression of Carrier	CL	(Note 7)	40	50	—	dB	4
Suppression of 2nd Carrier	I_{2nd}	(Note 8)	40	50	—	dB	4
920KHz Beat Level	I_{920}	(Note 9)	33	38	—	dB	4
Differential Phase	DP	(Note 10)	—	3.5	5	deg	5
Differential Gain	DG	(Note 10)	—	7	10	%	5
VIF Input Impedance	R_{IN} (VIF)	(Note 11)	1.5	3.0	6.0	$K\Omega$	6
	C_{IN} (VIF)		—	3.0	10.0	pF	
AFT Sensitivity	$\Delta F/V_{13-14}$	(Note 12)	—	16	—	kHz/V	2
AFT Output Voltage	Upper V_{13U} V_{14U}	(Note 13)	11.7	11.9	12.0	V	2
	Lower V_{13L} V_{14L}	(Note 13)	1.8	2.3	2.8	V	2
RF AGC Max Available Current	I_A Max	$SW_1: 1$ (KA2914A) $SW_2: 1$	0.3	—	—	mA	1
		$SW_1: 2$ $SW_2: 1$ (KA2918)	7.0	—	—		
RF AGC Delay Setting Range	V_{IN} Delay	(Note 14)	5	7	9	V	
AFT Band width	ΔF_W	(Note 13)	1.4	—	—	MHz	2
Video Output Voltage	V_{OUT}	(Note 15)	2.25	2.50	2.75	V	2

ELECTRICAL CHARACTERISTICS

SIF Section ($T_a = 25^\circ\text{C}$, $V_{CC} = 12\text{V}$, $f_p = 45.75\text{MHz}$, $f_s = 41.25\text{MHz}$)

Characteristic	Symbol	Test Conditions	Min	Typ	Max	Unit	Test Fig
SIF Output Voltage	S_{OUT}	(Note 16)	200	400	600	mV_{rms}	3
Input Limiting Voltage	$V_{IN(LIM)}$	(Note 17) $R_D = \infty$	—	200	400	μV_{rms}	8
AM Rejection Ratio	AMR	SIF IN: $f = 4.5\text{MHz}$ $f_m = 400\text{Hz}$, $\Delta f = \pm 25\text{kHz}$ AM 30%, $V_{IN} = 100\text{dBu}$	40	45	—	dB	8
Recovered Output Voltage	V_{OD}	SIF IN: $f = 4.5\text{MHz}$ $f_m = 400\text{Hz}$, $\Delta f = \pm 25\text{kHz}$ $V_{IN} = 80\text{dBu}$, $R_D = 12\text{k}\Omega$	0.5	0.75	—	V_{rms}	8
Total Harmonic Distortion	THD_{DET}	SIF IN: $f = 4.5\text{MHz}$ $f_m = 400\text{Hz}$, $\Delta f = \pm 25\text{kHz}$ $V_{IN} = 80\text{dBu}$	—	1.0	—	%	8
Max. Audio Output Voltage	V_{OM}	SIF IN: $f = 4.4 \sim 4.6\text{MHz}$	4.0	—	—	V_{p-p}	8
SIF Input Impedance	$R_{IN(SIF)}$	$f = 4.5\text{MHz}$	10.0	20.0	30.0	$\text{K}\Omega$	7
	$C_{IN(SIF)}$		—	3.0	—	pF	
DET Output Impedance	$R_O(DET)$	(Note 18)	10.0	15.0	20.0	$\text{K}\Omega$	9
DC Voltage	Terminal 21	SW_1 : 1 (KA2914A) 2 (KA2918)	3.5	4.4	5.3	V	1
	Terminal 23		4.8	6.0	7.2	V	
	Terminal 1	SW_2 : 2	6.0	6.7	7.4	V	
Max. Attenuation	ATT Max	(Note 19)	60	—	—	dB	10
DC Volume Gain	$G_{ATT \text{ Min}}$	$R_A = 0$ $G_{ATT \text{ Min}} = 20 \log \frac{V_2}{V_{23}}$	-5.5	-3.5	-1.5	dB	10
ATT Characteristics	1	$V_1(1)$	3.4	3.8	4.2	V	10
	2	$V_1(2)$	4.5	4.9	5.3	V	10
Signal Leakage	V_{PT}	(Note 20)	—	1.0	3.0	mV_{rms}	11
AF AMP. Gain	$G_V \text{ AF}$	(Note 21)	—	20	—	dB	13
AF AMP. Distortion	$THD \text{ AF}$	$P_{23A} = 1V_{pp}$, 400Hz SW_3 : On ATT: -26dB Setting	—	1.5	—	%	12
AF AMP. Max. Output Voltage	$V_{OAF \text{ Max}}$	(Note 21) $THD_{AF} 5\%$	1.5	2.0	—	V_{rms}	13
AF Output DC Voltage	V_3	SW_1 : 1 (KA2914A) 2 (KA2918) SW_2 : 2	6.7	7.7	8.8	V	1

* Read the 400Hz component of V_{AI} at P_2 with $R_A = 0$, set R_A so that $V_{AI} = 1/2 V_{AI} (-6\text{dB})$, then read DC voltage of terminal 1 (V_1).

** Read the 400Hz component of V_{AI} at P_2 with $R_A = 0$. Set R_A so that $V_{AI} = 3.16 \times 10^{-3} V_{AI} (-50\text{dB})$ then read DC voltage of terminal 1 (V_1).

TEST CIRCUIT

1. DC Characteristic




Fig. 1

2. AC Characteristic




Fig. 2

3. Video Frequency Response and SIF Output Voltage




Fig. 3

4. Inter Modulation





Fig. 4

5. DG, DP



APL = 50%
ATT: ADJUST SYNC TIP LEVEL TO DC 2.5V

Fig. 5

6. VIF Input Impedance




Fig. 6

7. SIF Input Impedance




Fig. 7


8. $v_{IN(LIM)}$, AMR, V_{OD} , THD, v_{OM} 

Fig. 8

9. Audio Output Impedance




Fig. 9


10. ATT MAX., $G_{ATT MIN}$, $V_1(1)$, $V_1(2)$ 

Fig. 10


11. V_{PT} 

Fig. 11


12. THD_{AF} 

Fig. 12


13. $G_v AF, V_{OAF MAX}$ 

Fig. 13

TEST CONDITIONS

Note 1) V_{AGC} (P5 EXT. Applying voltage) = 11.5V

VIF in: $f = 45.75\text{MHz}$ 1kHz 30% AM modulation

Adjust the VIF input level v so that the detected output of P15A with high impedance probe will be $0.8V_{p-p}$ and measure the input level.

Note 2) $V_{AGC} = 4V$

Measure VIF input level v same as note 1

$$\Delta A = 20 \log \frac{v}{V} \text{ (dB)}$$

Note 3) VIF IN: $f = 45.75\text{MHz}$ CW 15mVrms

Measure the DC level of P15

Note 4) VIF IN: $f = 45.75\text{MHz}$ APL 100%, 87.5% AM modulation.


P5: open

(1) Adjust the VIF input level 50mV_{p-p} and measure the detected output level v_{01p-p}

(2) Then increase the input level so that the detected output level will be $1.1 \times v_{01p-p}$ and measure the input level.

Note 5) $V_{AGC} = 8V$

VIF in: $f = 45.75\text{MHz} \pm 10\text{MHz}$ variable or sweep 15mVrms measure the DC level of P15.



Note 6) $V_{AGC} = 8V$ (GR $\approx 30\text{dB}$)

SG₁: 45.75MHz CW

SG₂: 45.75 ~ 40MHz variable

(1) Setting output of SG₁ so that the DC level of P15 will be 4.0V

(2) Setting output off SG₂ (45.75MHz) so that the AC level of P15 will be $0.5V_{p-p}$

(3) Decreasing frequency of SG₂ until the AC level of P15 will be $0.35V_{p-p}$ (-3dB of $0.5V_{p-p}$) then read $f_{SG2} = F$ $f_{BW} = 45.75 - F$ MHz

Note 7) SG₁: 45.75MHz, 1kHz 80% AM modulation 100mVrms

SG₂, SG₃; off

Setting V_{AGC} so that the output AC level of P15 will be $2.7V_{pp}$

Measure CL of P15 after setting to 0% AM of SG,

$$CL = 20 \log \frac{2.7}{V_{CB} (V_{P-P})} \text{ (dB)}$$

Note 8) Measure I_{2nd} of P15 the same as note 7

Note 9) $V_{AGC}=8V$

SG₁: 45.75MHz (P: picture) 100mVrms

SG₂: 41.25MHz (S: sound) 32mVrms (-10dB of SG₁)

SG₃: 42.17MHz (C: chroma) 32mVrms (−10dB of SG₁)

(1) Setting V_{AGC} so that the output tip level (lower) of P15 will be 3.0V DC

(2) Measure the level difference (dB) between the C-level and 920kHz level

Note 10) $V_{AGC} = 8V$

VIF IN: f=45.75MHz video signal (RAMP) 87.5% AM 100mV_{p-p}

Setting ATT so that the SYNC TIP level of P15 will be 2.5V DC.

Measure DP and DG

Note 11) $V_{AGC}=5V$ $f=45.75MHz$

Measure R_{IN} , C_{IN}

Note 12) AFT sensitivity $\Delta F/\Delta (V_{13}-V_{14})$

(1) INT, AGC (P5 open)

(2) VIF input: 45.75MHz $\pm$ 1.0MHz, CW 15mVrms

(3) Read the frequency (f_1) of VIF when $V_{13}-V_{14} = -IV$

(4) Read the frequency (f_2) of VIF when $V_{13}-V_{14}=1V$ then calculate

$$\Delta F / \Delta (V_{13} - V_{14}) = |f_1 - f_2|$$


Note 13) $\Delta F_W, V_{13U}, V_{14U}, V_{13L}, V_{14L}$

(1) INT AGC (P5 open)

(2) VIF IN: 45.75MHz±10MHz CW 15MVrms

(3) 8pF at Pin 16 should be shorted

(4) Read the frequency (f_1 or f_2) when the V_5 or V_6 is reduced to 90% of the f_0 of A or B with varying the frequency. Then the band width is the difference from center frequency (f_0).



Note 14) P5: Open

VIF IN: 45.75MHz CW 20mVrms

(1) Adjust the voltage of Terminal 3 so that the voltage of Terminal 4 will be 6.0V DC

(2) Measure the voltage of Terminal 3

Note 15) P5: Open

VIF in: 45.75MHz 100% APL 87.5% AM modulation signal amplitude 50mV_{p-p} Measure the detected output voltage (White peak to sync tip)

Note 16) P5: Open

SG₁: 45.75MHz CW 100mVrms

SG₂: 41.25MHz CW 25mVrms

Measure SIF (4.5MHz) output voltage at P15

Note 17) SIF IN: f=4.5MHz FM f_{MOD}=400Hz Δf=±25kHz,

(1) Adjust the SIF input level 100mV_{p-p} and measure the detected output level v_{OS}

(2) Then decrease the input level so that the detected output level will be 3dB down of V_{OS} and measure the input level

Note 18) Output impedance

(1) SIF IN: f=4.5MHz f_{MOD}=400Hz, Δf=±25kHz, 80dBμ

(2) At P23 read the V₀₁ at R_X = , then read the R_X when the recovered output becomes V_{01/2} by varying the R_X. The R_X is the output impedance.

Note 19) ATT MAX

(1) SIF in: f=4.5MHz, f_{MOD}=400Hz, f=±25kHz, 80dBμ

(2) Read the 400Hz component of V_{A1} at P2 with R_A=0, then read V_{A1}' with R_A=∞

$$ATT\ MAX = 20 \log \frac{V_{A1}}{V_{A1}'}$$

Note 20) U_{PT}

(1) SIF IN: f=4.5MHz, f_{MOD}=400Hz, Δf=±25kHz, 80dBμ

(2) Read the 400Hz component at P3

Note 21) G_V AF

(1) Apply 400Hz 0.1Vrms signal to P2

(2) Read the output voltage at P3

TYPICAL APPLICATION CIRCUIT

